

AJ-VHFBRIDGE-W

Ajax



Features

- Ajax
- Module for connecting to Ajax third-party VHF transmitters
- 868MHz Jeweller Wireless
- Bidirectional
- Internal antenna range open space 1800 m
- 8 potential outputs
- High/low potential outputs
- Transmits in pulse or bistable
- 220 VAC power supply and 12VDC to 4 or 7 Ah backup battery (not included)
- Compatibility with Hub 2, Hub 2 Plus and Hub Hybrid
- Compatibility with any VHF transmitter with relay inputs
- White colour

Specifications

Brand	Ajax
Frequency	868 MHz Jeweller
Transmission distance	Hatsa 1800 meters
Potential outlets	Up to 8
Types of outlets	High potential and low potential
Transmission types	Impulse and bistable
Supported events	<ol style="list-style-type: none">1. Intrusion2. Panic button3. Malfunctions4. Sabotage5. Loss of power supply to VHFBRIDGE6. Loss of HUB power supply7. HUB battery discharged8. Loss of connection between VHFBRIDGE and the HUB9. Fire10. Medical assistance11. Any alarm12. Change of security modes13. Discharged VHFBRIDGE battery14. Confirmed intrusion15. Emergency button alarm acknowledged
Support for photo verification of alarms	Not available
Compatibility with third-party VHF radio transmitters	Any VHF transmitter with relay inputs
Recommended transmitters	Hawk VHF Alarm Transmitter (FSK Electronics) TX750C (RDC) TR-41 (Puper)
Compatibility	Compatible with Hub 2, Hub 2 Plus, Hub Hybrid, ReX and ReX 2
Power	110–240 V~, 50/60 Hz
Backup battery	Battery 12 V / 4 or 7 Ah (not included)
Temp. operation	-10 °C ~ 40 °C
Dimensions	238 (H) x 192 (W) x 100 (D) mm
Dimensions of the backup battery	150 (H) x 64 (W) x 94 (D) mm
Colour	White