

**EN54** EN54 Internal Battery (24h/72h)

More ▾

### Tech specs

EN54 LINE

# EN54 Internal Battery (72h)

Rechargeable Li-ion battery (7.4 V/10 Ah) to install into EN54 Fire Hub Jeweller or EN54 Fire ReX Jeweller



Device compatibility

Check

---

## Battery type

## Battery

8 × 18650

Rechargeable Li-ion battery.

## Nominal voltage

7.4 V<sub>nom</sub>

## Capacity

10 Ah

---

## Power supply

### Maximum load current

3.2 A

### End-of-life battery voltage

6 V<sub>min</sub>

---

## Power consumption

### Average power consumption with LTE only

50 mAh

## **Average power consumption with Ethernet only**

120 mAh

## **Average power consumption with Wi-Fi only**

70 mAh

## **Average power consumption with Ethernet and Cellular (standby)**

102 mAh

## **Average power consumption with LTE, Wi-Fi, and Ethernet**

140 mAh

## **Recommendations**

Use the battery with compatible devices only.

The battery is designed for indoor use only.

Recommended replacement interval: 5 years.

---


## **Enclosure**

## Dimensions

166 × 87 × 23 mm

## Weight

443 g



## Operating temperature range

from -10 °C to +40 °C

## Operating humidity

up to 75% non-condensing



## Protection class

IP20

---

## Color

Black



White



## Complete set

EN54 Internal Battery (72h)

---

## Revision

2

## Certification and compliance with standards

 EN54 Internal Battery (72h)



## Additional information

### Compliance with standards

[Learn more >](#)

### User manual

[Learn more >](#)

### Warranty

24 months

[Learn more >](#)

### Subscribe

Subscribe to our emails about secure life. No spam.

[Subscribe](#)

### Request extra help

✉ [support@ajax.systems](mailto:support@ajax.systems)

🗣️ [@AjaxSystemsSupport\\_Bot](#)

💬 [Send a request](#)



Rating 4.8

4,500,000

people worldwide under Ajax protection

💡 [Suggest a feature](#)



## Products

- Intrusion protection
- Video surveillance
- Fire and life safety
- Comfort and automation
- All products
- Services
- System integrations
- Ajax Ready products
- Fibra wired protocol
- Ajax radio protocols

## Solutions

- Customer stories
- Solutions by facility type
- Commercial fire detection and alarm system
- Wireless Grade 3 solution
- Video surveillance solution
- Integration with Yale smart locks
- Upgrades and retrofits
- Why Ajax
- How it works

## Software

- Ajax Security System
- Ajax PRO: Tool for Engineers
- Ajax Desktop
- Ajax PRO Desktop
- Ajax TV
- Ajax Translator PRO
- Ajax Cloud Signaling
- Scenarios



Available on  
**App Store**



Available on  
**Google Play**

## Support

- Manuals and articles
- Compliance with standards

## Tools

- Ajax device compatibility
- CMS software compatibility
- Ajax Services availability
- Video storage calculator
- Video device calculator
- Battery life calculator
- Radio communication range calculator
- Switches and outlets configurator
- Fibra power supply calculator
- All web tools

## Monitoring solutions and integrations

- Intrusion alarm monitoring
- Video monitoring and visual alarm verification
- Audio alarm verification

## Company

[Blog](#)  
[About us](#)  
[Press page](#)  
[Events](#)  
[Career](#)  
[Ajax Next](#)  
[Reviews and feedback](#)

## For partners

[For partners](#)  
[Ajax Academy](#)  
[Partner Portal](#)

 [Србија](#) [Privacy policy](#) [Report a vulnerability](#) [GDPR White Paper](#) [NDAA Statement](#) [Cookie policy](#)  
[Anti-Spam Policy](#) [Ajax Services T&C](#) [End user agreement](#) [Warranty](#)

© 2026 AJAX SYSTEMS CH. All rights reserved