



## BRAVO SR300 ALK Wireless Outdoor Siren

#### Description

BRAVO SR300 ALK is a wireless piezo siren for outdoor mounting designed for operation in BRAVO wireless intruder alarm systems or with ECLIPSE WL wireless expander module in ECLIPSE hybrid systems. The siren can be located in a distance up to 400m away from the control panel.

BRAVO SR300 ALK is equipped with sound and LED indication for announcing of alarm events, inner metal casing and bidirectional tamper for higher protection. An external adapter 12VDC/1A may be used to power the siren and prolong the battery life. The siren has a flat plastic cover, which is especially suitable for company sticker or logo. BRAVO SR300 ALK wireless siren is designed according the requirements and covers the standard EN50131, GRADE 2, Class II.

Tel.:+359 2 9694 800

Fax: +359 2 9625 213

#### Technical Specifications

Battery.....4x1.5V, alkaline

Battery life . . . . . . . . . . 3 years\*

Battery low voltage signal. . . . . . signal sent at value < 5.1VDC

Operation frequency . . . . . . . . . . . . . . . . . . 868MHz
Radio distance (open space) . . . up to 400m
Loudspeaker type . . . . . . . . piezo
Protection of the housing . . . . . IP44/IK04
Protection of the electronics . . . IP55
Programmable alarm cycle . . . . 1-3 minutes

Housing . . . . . . . . . . . ABS plastic box with inner metal cover


Operation temperature  $\dots -10^{\circ}\text{C} \div +40^{\circ}\text{C}$ Sound volume  $\dots \dots 110 \text{dB/1m}$ 

Weight.....∼1.240kg

\* Based on normal use of the siren (e.g. 1 alarm per month with strobe and 1 minute alarm cycle, and 8 squawks per day at an average of 25°C). If the use is more frequent or the alarm cycle is set for more than 1 minute the battery life may be reduced. Using optional power supply with adapter 12V/1A will extend the battery life.

### Functional Specifications

- Suitable for outdoor mounting
- Bi-directional tamper switch for self-protection of the box
- Separate alarm notifications for intrusion and fire
- Squawk functionality
- Reset button for restoring the factory settings
- Internal metal cover for increased protection
- Plastic cover for protection of the electronic components
- Additional external power supply with adapter
- Chasing LEDs optional switching









# **BRAVO SR300 ALK Wireless Outdoor Siren**

- Packing Information
  - •Single packing box 1 unit BRAVO SR300 ALK, dimensions 332 x 238 x 67mm
  - Master packing box 5 units BRAVO SR300 ALK, dimensions 360 x 345 x 252mm
- Compatible Product Range
  - •BRAVO EXT Wireless panel with external power supply
  - BRAVO INTR Wireless panel with built-in power supply
  - ECLIPSE WL Wireless expander module for ECLIPSE control panels

Contact Information

Tel.:+359 2 9694 800

Fax: +359 2 9625 213