

Wireless panic button



- Bi-directional communication
- Included lanyard
- Compact design

PAX Panic remote control is a panic button with a detachable lanyard. Pressing the red button generates a "PANIC" type event in the control panel.

PAX Panic is compatible for operation with:

- BRAVO Next wireless control panel, for building of fully wireless security systems.
- PAX WL Expander module, for building of hybrid security systems with Eclipse series control panels.

Features

- Bi-directional type for wireless communication
- Jamming detection and communication channels encryption
- Wireless communication range(open space) - up to 1500m
- Standard type of batteries – CR2032
- Dual-button key fob for sending a panic alarm
- Lanyard, included

Technical Specifications

Operation frequency:	~ 868MHz
Communication type:	Bi-directional
Low voltage threshold	2.4 V
Absorbed current (Standby)	16 mA / 2 μ A
EMC Immunity	EN 50130-4
Number and type of batteries	1 x CR2032
Battery life	~ 4 years
Operating temperature range:	from -10°C to +50°C
Color	Black
Dimensions	66 x 35 x 12 mm