

AJ-TRANSMITTER

Ajax



Features

- Ajax
- Transmitter via radio
- 868MHz Jeweller Wireless
- Bidirectional
- Internal antenna range open space 1600 m
- Wired alarm input and anti-sabotage tamper
- Inhibition detection
- Tamper-resistant opening
- Power output 3.3 V
- Power supply 3 batteries CR123A 3.0 V
- Compatibility with third-party detectors with wired alarm output

Specifications

Brand	Ajax
Certified	Grade 2
Frequency	868 MHz Jeweller
Transmission distance	? 1600 m in open space
Anti-inhibition detection	Available
Alarm input	Available. NO/NC (Configurable)
Tamper input	Available. NO/NC (Configurable)
Tamper-resistant opening	Accelerometer
Power supply output	3.3 V
Advanced features	KeyArm Zone
Temp. operation	-25 °C ~ 50 °C
Battery	3 batteries CR123A 3.0 V
Dimensions	100 (H) x 39 (W) x 22 (D) mm