

XS-KB5000NK

X-Security IP Control Keyboard

LCD touch screen 10"

Connection RS485 / RS422 / RJ45 /
RS232

WiFi | Ethernet | USB | HDMI

4-axis joystick and mini keyboard

Up to 4 channels 4K or 16 of 1080p



X-Security

IP Keyboard

To control DVRs, NVRs and motorised domes from X-Security

USB Connection, RS232, RS485, RS422, Red and WiFi

Joystick 4 axis (zoom, focus and iris)

LCD 10.1" touch screen to preview 4K in real time

4 HDMI outputs

Decoding up to 4 channels at 12Mpx

Supports capture and local recording on USB pin

Audio and alarms

Keypad module included

Specifications

Brand	X-Security
Processor	Dual-core Braswell Processor
Operating system	Embedded LINUX 4.2.0
Communication mode	2x USB 3.0 / 2x USB 2.0 / RS485 / 2xRS232 / RS422 / 2xRJ45 (10/100/1000M) / WiFi
Display	Touch screen 10.1" LCD (1280x800)
Video outputs	4x HDMI
Resolution	4CH@12MP(20fps)/4CH@4K(30fps)/6CH@5MP(30fps)/8CH@ 4MP(30fps)/10CH@3MP(30fps)/16CH@2MP(30fps)
Compression	H.265/H.264+/H.264/MJPEG
Bidirectional audio	1 Jack Line IN/ 1 Jack Line OUT / Integrated speaker
Alarms	4 IN/ 4 OUT (3xrelay / 1x12V1A)
Power	DC 12 V / 4 A
Dimensions	59 (h) x 425 (w) x 194 (d) mm / Mini keyboard:26 (H) x 421 (W) x 105 (D) mm
Weight	3730 g